



ANSI C82.77-10-2021

*American National Standard for Lighting Equipment—
Harmonic Emission Limits—
Related Power Quality Requirements*

Secretariat:

National Electrical Manufacturers Association

Approved: August 27, 2021

American National Standards Institute, Inc.

NOTICE AND DISCLAIMER

The information in this publication was considered technically sound by the consensus of persons engaged in the development and approval of the document at the time it was developed. Consensus does not necessarily mean that there is unanimous agreement among every person participating in the development of this document.

ANSI Standards and guideline publications, of which the document contained herein is one, are developed through a voluntary consensus Standards development process. This process brings together volunteers and/or seeks out the views of persons who have an interest in the topic covered by this publication. While NEMA administers the process to promote fairness in the development of consensus, it does not write the document and it does not independently test, evaluate, or verify the accuracy or completeness of any information or the soundness of any judgments contained in its Standards and guideline publications.

NEMA disclaims liability for any personal injury, property, or other damages of any nature whatsoever, whether special, indirect, consequential, or compensatory, directly or indirectly resulting from the publication, use of, application, or reliance on this document. NEMA disclaims and makes no guaranty or warranty, expressed or implied, as to the accuracy or completeness of any information published herein, and disclaims and makes no warranty that the information in this document will fulfill any of your particular purposes or needs. NEMA does not undertake to guarantee the performance of any individual manufacturer or seller's products or services by virtue of this Standard or guide.

In publishing and making this document available, NEMA is not undertaking to render professional or other services for or on behalf of any person or entity, nor is NEMA undertaking to perform any duty owed by any person or entity to someone else. Anyone using this document should rely on his or her own independent judgment or, as appropriate, seek the advice of a competent professional in determining the exercise of reasonable care in any given circumstances. Information and other Standards on the topic covered by this publication may be available from other sources, which the user may wish to consult for additional views or information not covered by this publication.

NEMA has no power, nor does it undertake to police or enforce compliance with the contents of this document. NEMA does not certify, test, or inspect products, designs, or installations for safety or health purposes. Any certification or other statement of compliance with any health- or safety-related information in this document shall not be attributable to NEMA and is solely the responsibility of the certifier or maker of the statement.

AMERICAN NATIONAL STANDARD

Approval of an American National Standard requires verification by the American National Standards Institute, Inc. (ANSI) that the requirements for due process, consensus, and other criteria for approval have been met by the Standards developer. An American National Standard implies a consensus of those substantially concerned with its scope and provisions. Consensus is established when, in the judgment of the ANSI Board of Standards Review, substantial agreement has been reached by directly and materially affected interests. Substantial agreement means much more than a simple majority, but not necessarily unanimity. Consensus requires that all views and objections be considered, and that a concerted effort be made toward their resolution. The existence of an American National Standard does not in any respect preclude anyone, whether s/he has approved the Standards or not, from manufacturing, marketing, purchasing, or using products, processes, or procedures not conforming to the hard-wired. It is intended as a guide to aid the manufacturer, the consumer, and the general public.

The American National Standards Institute, Inc., does not develop Standards and will in no circumstances give an interpretation of any American National Standard. Moreover, no person shall have the right or authority to issue an interpretation of an American National Standard in the name of the American National Standards Institute, Inc. Requests for interpretations should be addressed to the Committee Secretariat referred to on the title page.

CAUTION NOTICE: This American National Standard may be revised or withdrawn at any time. The procedures of the American National Standards Institute, Inc., require that action be taken periodically to reaffirm, revise, or withdraw this Standards. Purchasers of American National Standards may receive current information on all Standards by calling or writing the American National Standards Institute, Inc.

Published by

National Electrical Manufacturers Association
1300 North 17th Street, Suite 900
Rosslyn, Virginia 22209

© 2021 National Electrical Manufacturers Association

All rights, including translation into other languages, reserved under the Universal Copyright Convention, the Berne Convention for the Protection of Literary and Artistic Works, and the International and Pan American copyright conventions.

No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without prior written permission of the publisher.

Printed in the United States of America

Foreword (This foreword is not part of ANSI C82.77-10-2021.)

This is not a new Standard, and is a revision of ANSI C82.77-10-2020.

Suggestions for improvement of this Standard are welcome. They should be submitted to:

Secretary, ASC C82
National Electrical Manufacturers Association
1300 North 17th Street, Suite 900
Rosslyn, Virginia 22209

This Standard was developed and approved for submittal to ANSI by the C82 Committee. Approval of this Standard is not meant to imply that all Committee Members voted to approve it.

Contents

1	Scope	1
1.1	Normative References	1
2	General Considerations	2
3	Specific Lighting Equipment Emission Limits by Product Type and Application	2
3.1	Residential Lighting Equipment	2
3.1.1	Integrally Ballasted Medium Screw Base Light Sources	2
3.1.2	Indoor Hard-Wired Luminaires and Indoor Portable Luminaires	4
3.1.3	Leading-Edge Phase Controlled Dimming Devices	5
3.1.4	Trailing-Edge Phase Controlled Dimming Devices	5
3.1.5	System Point of Common Coupling Requirements (PCC)	5
3.1.6	Outdoor Residential Applications	5
3.2	Commercial Lighting Equipment for General Lighting	5
3.2.1	Integrally Ballasted Medium Screw Based Light Sources	5
3.2.2	Indoor, Hard-Wired Ballasts, Hard-Wired LED Drivers or Luminaires	7
3.2.3	Task Lighting and Down Lighting and Modular Office Furniture	7
3.2.4	Phase Controlled Dimming Devices	8
3.2.5	Luminaires Rated for Outdoor Use	8
3.2.6	System Point of Common Coupling Requirements (PCC)	8
3.3	Industrial Lighting Equipment for General Lighting Applications	8
3.3.1	Indoor Hard-Wired Fluorescent Ballasts or Luminaires	8
3.3.2	Indoor or Outdoor Hard-Wired HID Ballasts or Luminaires	8
3.3.3	Indoor or Outdoor Hard-Wired LED Drivers or Luminaires	8
3.3.4	Other Lighting Equipment	9
3.3.5	System Point of Common Coupling Requirements (PCC)	9
3.4	Roadway, Sports Arena, and Convention Center Lighting Equipment	9
3.5	Stage and Studio Lighting Equipment	9
4	Testing and Measurements—General	10
5	Measurement Methodology for Type Testing of Products	10
5.1	General	10
5.2	Mathematical Formulae	10
5.3	Voltage Stability	11
5.4	Power Supply Internal Impedance	11
5.5	Current Sensors	12
5.6	Power Analyzer Setup	12
	Annex A (Normative)	14
	Annex B (Informative References)	15
	Annex C (Informative)—The Effect of Product Efficiency on the Input Current versus Power Factor for Different Technologies	16

< This page left blank intentionally. >

1 Scope

This Standard specifies power quality limits, factors, and methods of measurement for lighting equipment. This Standard covers all types of lighting equipment that is used for general illumination (typically found in residential, commercial, and industrial applications) and which is connected to any of the following commonly distributed 60 Hz alternating current (AC) power line systems:

- 120 V, Single Phase
- 220/230 V, Single Phase
- 208/240 V, Single Phase
- 277V, 347 V, Single Phase
- 480 V, Single Phase
- 480V/347 V, 3 Phase

NOTE: These line voltages are nominal and include commonly encountered nameplate variations of the above. As an example, products rated at either 117, 120, or 125 Volts AC would be covered as being inclusive of nominal 120 V systems.

Harmonic emission limits, where they are defined by this Standard, shall include harmonic emissions over the low-frequency range 0–9 kHz.

This Standard covers lighting equipment regardless of wattage (operating input power level) or operating input current. However, emission limits will only be specified over a range of power or current.

This Standard supersedes the requirements for power factor (PF) and total harmonic distortion (THD) of ANSI C82.11, ANSI C82.14, and ANSI C82.16.

Depending upon the specific product, harmonic limits in this Standard may be expressed in terms of THD rather than individual limits for specific harmonics. Since there is a technical relationship between power quality parameters, some products will include PF, harmonic distortion factor, or displacement factor requirements, where the addition of these criteria is helpful to set a baseline for power quality impact of lighting equipment. Emphasis has been on establishing relatively simple limits to assess and that are in keeping with the practices of this industry. Alternatively, power quality and emissions are expressed in terms of displacement factor and harmonic distortion factor.

Lighting equipment covered under the scope of this Standard, which contains only passive electrical components or passive ballast circuitry, is exempt from limits and need not be measured or tested, i.e., core and coil ballasts.

Note: As an example, an electronic starter (which contains an electronic component) is sometimes used in conjunction with passive ballast circuitry. The overall device or equipment would still be classified as a passive ballast circuit.